5828

WIRELESS FIXED ENGLISH KEYPAD



A perfect add-on to any LYNX or residential VISTA system, the 5828 wireless keypad saves dealers valuable time by offering the quickest, easiest installation of a secondary keypad. The 5828 is easy and inexpensive to install, with no wires to run. It mounts anywhere—on walls, tabletops and counters—and provides the flexibility and convenience of operating the system from anywhere in the home.

FEATURES

- No wires to run-lower installation time and labor costs
- Compatible with LYNX and residential VISTA systems (VISTA-10P, 15P, 20P and 21iP)
- Includes three AA batteries or optional AC power pack for "always on" operation
- Large, easy to use keypad with single button operation
- · Optional desk mount

- Attractive white console blends perfectly with any décor
- Contoured, removable door conceals soft-touch illuminated keys

SPECIFICATIONS

Physical

6-1/4" W x 4-3/4" H x 1-3/8" D (159mm x 121mm x 35mm)

Frequency of Operation

345MHz

Sounder

Speaker

Electric

110VAC input, 5.0V Regulated DC output, 220mA

Batteries

Three 1.5V, AA, Alkaline

ORDERING

5828 Wireless Fixed English Keypad

5828V Wireless Talking Fixed English Keypad5828DM Includes Desk Mount and AC Adapter

Automation and Control Solutions

Honeywell Security & Communications 2 Corporate Center Dr. Suite 100 P.O. Box 9040 Melville, NY 11747 1.800.467.5875 www.honeywell.com



L/5828D/D July 2011 © 2011 Honeywell International Inc.